



DATE: December 2, 2008  
FOR IMMEDIATE RELEASE

### CIT Relay & Switch announces RoHS, UL Listed, Process Sealed BSP Series Sub-Miniature Pushbutton

**Minneapolis, Minnesota** – CIT Relay & Switch announces the availability of the BSP Series sub-miniature momentary pushbutton switch. Offering numerous terminals including snap-in mounting options, the BSP provides design engineers a versatile, momentary switch for use in wide variety of applications. Available in both Single Pole and Double Pole, the BSP offers a choice in of silver-plated, gold-plated or gold over silver-plated contacts.

Specifications: Electrical rating is 3A @ 120VAC and 28VDC, 1A @ 250VAC. Typical electrical life is 30,000 cycles. Contact Resistance is <20mΩ maximum initially at 2~4VDC, 100mA. Dielectric Strength is 1000Vrms minimum with Insulation Resistance of >1000MΩ minimum. Operating and Storage Temperature is -40°C to 85°C, sealed to IP67 standards. SPDT or DPST configuration.

Materials: RoHS Compliant. Actuator is Thermoplastic Polyester with housing of 6/6 Nylon, glass filled, flame retardant, heat stabilized (UL94V-0). The bracket is tin plated brass. Contacts and terminal options: silver-plated copper alloy, gold for dry circuit less than .4 volt amps, or gold over silver. Round or square caps in standard colors of red, black or white are available as standard

Lead-time averages 4 to 6 weeks. Volume pricing ranges from **\$1.18**, dependent on option choices. Contact us directly for a quote and sample to solve your toggle switch needs.

Typical applications of the BSP Series switch include consumer electronics, instrumentation telecommunications, test equipment, computer and computer peripheral, security, audio, medical and wherever applications require sub-miniature process sealed switching.

*CIT RELAY & SWITCH*, a division of Circuit Interruption Technology, Inc., manufactures a broad array of automotive, telecom, security, industrial and audio relays and switches in thru-hole, panel, and surface mount styles. *CIT RELAY & SWITCH* products are supported by a worldwide network of distributors and sales representatives. For more information about the *CIT RELAY & SWITCH* BSP Series Sub-Miniature Pushbutton Switch or any of the CIT switch or relay products, contact *CIT RELAY & SWITCH*, 1152 Highway 10 NE, Minneapolis, MN 55432. Phone: 763-535-2339, Fax: 763-535-2194, E-Mail: sales@citswitch.com, Website: www.citswitch.com

Direct Link: <http://www.citrelay.com/Catalog%20pages/Switches/BSP%20Catalog.pdf>

Press Release Contact: Doreen Leppa  
dleppa@citrelay.com  
763-535-2339

Sales & Engineering Contact: Tony Schisler  
tschisler@citrelay.com  
763-535-2339

CIT Relay & Switch  
1152 Highway 10 NE  
Minneapolis, MN 55432  
763-535-2339  
www.citswitch.com  
sales@citswitch.com

